







Fingerprint Management System

Quick Operation Manual






SYSOFT-FPM Setup

1. Put in SYRIS software cd to CD-ROM, and run  SYFPM_Setup . The screen will show the form of Setup.
2. The setup wizard form will be shown. Please click  to continue.
3. If you want to setup the program into folder that is different from default, you can click setting then to select the destination folder by using  .
4. If you want to setup system into default folder, please click  directly.
5. System will show all of the setting before start to copy installation file into system. You can check them and if the setting is correct, you can click  to install system.
6. Click  to complete the installation process.

Import Card Data · Basic Data into SYSOFT-FPM【Using SYW95A as Door Access System】

If the data source comes from SYW95A, the operation process as following :

1. Activate the system by clicking  on the desktop.
2. After confirming the path of CardV3.mdb 【 Default path is C:\Program Files\SYW95A-V3】. Please select【Fingerprint Device Card Management \ Access Data Import System(SYW95A)\Database Setting(SYW95A)】 to choice database. After selecting the database, please click  then click  to save the database path.

3. Select 【 Fingerprint Device Card Management\Access Data Import System(SYW95A) \Basic Data Setting(SYW95A)】 , check Card data · Holder data and Dept. data and chek each one the option to cover while the data is repeat.

【Notice】 If you don't use card to manage, you still need to simulate card to set to all holder. You can add card by access 【 Fingerprint Device Card Management\Access Data Import System(SYW95A)\Card Data Transmission

(SYW95A)] .

☞ Fingerprint Module Management :

1.If you want to record fingerprint by using SYRDF5(SYRDF6), please access **【Fingerprint Device Card Management\Fingerprint Card Setting\Fingerprint Device Setting】** to set Controller and Module. **【Please close SYSOFT-FPM and re-activate it after add/modify Controller or Module】** .

2.Please access **【Fingerprint Device Card Management\Fingerprint Card Setting/Card Data Transmission】** to transfer Card data to Controller in order to use fingerprint to access.

【Notice】 Upgrade SYFPM V1.0 into SYSOFT-FPM V2.0, and the new database needs to import data from old one, please access **【Fingerprint Device Card Management\Fingerprint Card Setting\Fingerprint Data Converter】** .

☞ Fingerprint Recorder Setting

1.Please confirm the source of fingerprint **【SYRDF5(SYRDF6) or Enroll(Desktop Fingerprint Module)】** by accessing **【Fingerprint Management System\Fingerprint Management\System Setting】** .

2. If the source is Enroll(Desktop Fingerprint Module), please run the Version switch and step by step by indication on form.

3.If the source is SYRDF5(SYRDF6), please access **【Fingerprint Management System\Fingerprint Management\Fingerprint Link Setting】** .

☞ Add 、 Delete 、 Transfer and Print Fingerprint Data

1. **【Fingerprint Management System\Fingerprint Setting \Fingerprint Setting】** : It provides functions to create 、 delete or modify fingerprint. It also provides setting 、 getting and anti-duress setup by using SYRDF5(SYRDF6) or Enroll(Desktop Fingerprint Module).

2. 【 Fingerprint Management System \ Fingerprint Setting \ Fingerprint Transmission】 : Transfer fingerprint to specific module.

3. 【Fingerprint Management System\Fingerprint Setting\Fingerprint Browser】 : Print Fingerprint Report.

Please click link of Help in software to refer detail operation process.

