

SYLINK-R-M1

Desktop Reader / Card Writer



- The serial number can be filled-in the format of Decimal or Hexadecimal .
- Able to Display / Record card status of reading and card serial number.
- Read specific area of card via SYW95A/SYSOFT-95A.
- Keypro of SYW95A.



○ Specifications:

Specs / Item	SYLINK-R-M1
Frequency	125KHz(EM) / 13.56MHz (Mifare)
Read range	5~15cm / 2~6cm
Interface	RS232 , RS485 , USB
Baud rate	4,800~115,200 bps
Indicator	8 LED
ID	1~8(SYW95A) / 01~99 (SYSOFT-95A)
Tamper switch	Built-in
Operating TEMP.	-20°C~70°C
Power supply	8V~15V DC or USB
Dimensions (mm)	110 x 136 x 32.5mm

Ordering Information

Item	Type	Auto-detecting	
SYLINK-R-M1	Desktop Reader / Card Writer	SYW95A	Access Management Software
		SYSOFT-95A	Access Management Software



SYRIS Technology Corp.
 ACCESS CONTROL & RFID TOTAL SOLUTION
<http://syris.com> ; xtive.com.tw sales@syris.com